

I Claim:

- Sub A7
1. An electromagnetic antenna apparatus; the apparatus exhibiting a generally continuous signal response between a first frequency and a second frequency; the apparatus exhibiting a deviation from said signal response in a frequency region centered substantially at a selected frequency between said first frequency and said second frequency; the apparatus comprising:
 - (a) an antenna transceiving element;
 - (b) a feed structure; said feed structure being coupled with said antenna receiving element for communicating transceiving signals with said antenna transceiving element; and
 - (c) a discontinuity structure in said antenna transceiving element; said discontinuity structure being coupled with said feed structure; said discontinuity structure being configured for effecting return of selected said transceiving signals to said feed structure as return signals; said return signals effecting said deviation.
 2. An electromagnetic antenna apparatus as recited in Claim 1 wherein said antenna transceiving element has a polygonal shape defined by a periphery; said discontinuity structure including a first deviation structure interrupting said periphery at a first deviation locus displaced a first peripheral distance in a first direction along said periphery from said feed structure; said first deviation structure extending to a first return distance from said first deviation locus toward said feed structure; said first return distance being sufficient to establish signal coupling between said first deviation structure and said feed structure.
 3. An electromagnetic antenna apparatus as recited in Claim 2 wherein said selected frequency has a selected wavelength and wherein said first peripheral distance plus said first return distance substantially approximates one-half said selected wavelength.

1 4. An electromagnetic antenna apparatus as recited in Claim 2 wherein said
2 discontinuity structure further includes a second deviation structure interrupting said
3 periphery at a second deviation locus displaced a second peripheral distance in a
4 second direction along said periphery from said feed structure; said second deviation
5 structure extending to a second return distance from said second deviation locus
6 toward said feed structure; said second return distance being sufficient to establish
7 signal coupling between said second deviation structure and said feed structure.

1 5. An electromagnetic antenna apparatus as recited in Claim 4 wherein said selected
2 frequency has a selected wavelength and wherein said second peripheral distance plus
3 said second return distance substantially approximates one-half said selected
4 wavelength.

1 6. An electromagnetic antenna apparatus as recited in Claim 1 wherein said antenna
2 transceiving element has a substantially elliptical shape defined by a periphery having
3 a peripheral length; said elliptical shape being oriented substantially symmetrically
4 with respect to a major axis and a minor axis perpendicular with said major axis; said
5 discontinuity structure including a material-free zone within said periphery; said
6 material-free zone being delineated by a first border having a first edge length and a
7 second border having a second edge length greater than said first edge length and less
8 than said peripheral length; said first border and said second border meeting at a pair
9 of termini; each terminus of said pair of termini being situated sufficiently near said
10 feed structure to establish signal coupling between said deviation structure and said
11 feed region.

1 7. An electromagnetic antenna apparatus as recited in Claim 6 wherein said frequency
2 region is bounded by a lower frequency having a longer wavelength and by a higher
3 frequency having a shorter wavelength; and wherein said first edge length
4 approximates one-half said shorter wavelength and said second edge length
5 approximates one-half said longer wavelength.

2025-01-20 09:42:00

1 8. An electromagnetic antenna apparatus; the apparatus exhibiting a generally
2 continuous signal response between a first frequency and a second frequency; the
3 apparatus exhibiting a deviation from said signal response in a frequency region
4 centered substantially at a selected frequency between said first frequency and said
5 second frequency; the apparatus comprising:
6 (a) at least one antenna transceiving element;
7 (b) a feed structure for each respective antenna transceiving element of said at least
8 one antenna transceiving element; transceiving signals being communicated with
9 each said respective antenna transceiving element via a respective said feed
10 structure;
11 (c) a discontinuity structure in at least one selected antenna transceiving element of
12 said respective antenna transceiving element; said discontinuity structure being
13 coupled with said respective feed structure for said at least one selected antenna
14 transceiving element; said discontinuity structure being configured for effecting
15 return of selected said transceiving signals to said respective feed structure as
16 return signals; said return signals effecting said deviation.

1 9. An electromagnetic antenna apparatus as recited in Claim 8 wherein said at least one
2 selected antenna transceiving element has a polygonal shape defined by a periphery;
3 said discontinuity structure including a first deviation structure interrupting said
4 periphery at a first deviation locus displaced a first peripheral distance in a first
5 direction along said periphery from said respective feed structure; said first deviation
6 structure extending to a first return distance from said first deviation locus toward
7 said respective feed structure; said first return distance being sufficient to establish
8 signal coupling between said first deviation structure and said respective feed
9 structure.

1 10. An electromagnetic antenna apparatus as recited in Claim 9 wherein said selected
2 frequency has a selected wavelength and wherein said first peripheral distance plus

20250120 09:22:00

3 said first return distance substantially approximates one-half said selected
4 wavelength.

1 11. An electromagnetic antenna apparatus as recited in Claim 9 wherein said
2 discontinuity structure further includes a second deviation structure interrupting said
3 periphery at a second deviation locus displaced a second peripheral distance in a
4 second direction along said periphery from said respective feed structure; said second
5 deviation structure extending to a second return distance from said second deviation
6 locus toward said respective feed structure; said second return distance being
7 sufficient to establish signal coupling between said second deviation structure and
8 said respective feed structure.

1 12. An electromagnetic antenna apparatus as recited in Claim 11 wherein said selected
2 frequency has a selected wavelength and wherein said second peripheral distance plus
3 said second return distance substantially approximates one-half said selected
4 wavelength.

1 13. An electromagnetic antenna apparatus as recited in Claim 8 wherein said at least one
2 selected antenna transceiving element has a substantially elliptical shape defined by a
3 periphery having a peripheral length; said elliptical shape being oriented substantially
4 symmetrically with respect to a major axis and a minor axis perpendicular with said
5 major axis; said discontinuity structure including a material-free zone within said
6 periphery; said material-free zone being delineated by a first border having a first
7 edge length and a second border having a second edge length greater than said first
8 edge length and less than said peripheral length; said first border and said second
9 border meeting at a pair of termini; each terminus of said pair of termini being
10 situated sufficiently near said respective feed structure to establish signal coupling
11 between said deviation structure and said respective feed region.

1007740-0450

1 14. An electromagnetic antenna apparatus as recited in Claim 13 wherein said frequency
2 region is bounded by a lower frequency having a longer wavelength and by a higher
3 frequency having a shorter wavelength; and wherein said first edge length
4 approximates one-half said shorter wavelength and said second edge length
5 approximates one-half said longer wavelength.

1 15. An antenna apparatus for transceiving electromagnetic signals; the apparatus
2 exhibiting a generally continuous signal response between a first frequency and a
3 second frequency; the apparatus exhibiting a deviation from said signal response in at
4 least one frequency region; each respective frequency region of said at least one
5 frequency region being centered substantially at a respective selected frequency
6 between said first frequency and said second frequency; the apparatus comprising:
7 (a) at least one transceiving element;
8 (b) at least one feed structure; each respective said at least one transceiving element
9 transferring said electromagnetic signals via a respective feed structure of said at
10 least one feed structure;
11 (c) at least one selected transceiving element of said at least one transceiving element
12 including a discontinuity structure; said discontinuity structure being coupled with
13 said respective feed structure for effecting return of selected said transceiving
14 signals to said respective feed structure as return signals; said return signals
15 effecting said deviation.

1 16. An antenna apparatus for transceiving electromagnetic signals as recited in Claim 15
2 wherein said at least one selected transceiving element has a polygonal shape defined
3 by a periphery; said polygonal shape being generally symmetric about an axis; said
4 axis intersecting said respective feed structure; said discontinuity structure comprising
5 a plurality of material free zones in said polygonal shape; said plurality of material
6 free zones being arranged substantially symmetrically with respect to said axis; each
7 respective material free zone interrupting said periphery at a respective deviation
8 locus displaced a respective deviation distance along said periphery from said

2025-01-04 10:42:00

9 respective feed structure; each said respective material free zone extending a
10 respective return distance from said respective deviation locus toward said respective
11 feed structure; said respective return distance being sufficient to establish signal
12 coupling between said respective deviation structure and said respective feed
13 structure.

1 17. An antenna apparatus for transceiving electromagnetic signals as recited in Claim 16
2 wherein each said respective selected frequency has a respective selected wavelength
3 and wherein said respective peripheral distance plus said respective return distance
4 substantially approximates one-half of a respective selected wavelength.

1 18. An antenna apparatus for transceiving electromagnetic signals as recited in Claim 15
2 wherein said at least one selected antenna transceiving element has a substantially
3 elliptical shape defined by a periphery having a peripheral length; said elliptical shape
4 being oriented substantially symmetrically with respect to a major axis and a minor
5 axis perpendicular with said major axis; said discontinuity structure including a
6 material-free zone within said periphery; said material-free zone being bounded by a
7 first border having a first edge length and a second border having a second edge
8 length; said second edge length being greater than said first edge length and less than
9 said peripheral length; said first border and said second border meeting at a pair of
10 termini; each terminus of said pair of termini being situated sufficiently near said
11 respective feed structure to establish signal coupling between said deviation structure
12 and said respective feed region.

1 19. An electromagnetic antenna apparatus as recited in Claim 18 wherein said frequency
2 region is bounded by a lower frequency having a longer wavelength and by a higher
3 frequency having a shorter wavelength; and wherein said first edge length
4 approximates one-half said shorter wavelength and said second edge length
5 approximates one-half said longer wavelength.

2025 FEB 20 09:22:00